

# How to replicate a standard custom configuration to multiple TS3000i

63 [Frank Mateo](#) Mon, Jan 24, 2011 [How To's, Tricks, Tips](#) 0 4330

## How to replicate a standard custom configuration to multiple TS-3000i(s)

### Answer:

The following steps will allow you to generate a standard custom configuration setup from your initial clock and copy the settings via a file upload to any subsequent TS-3000i terminals.

To your original current TS-3000i clock, simply do the following:

1. Login to the clock's webpage
2. Utilities – backup/restore
3. Backup – configuration
4. shared
5. Run backup

**Note:** The backup will be generated in your ftp location which was specified in your utilities – settings section.

1. Login to the 2nd TS-3000i clock webpage
2. Setup the ftp settings same as the 1st TS-3000i clock
3. Select the Utilities – backup/restore
4. Select the Restore tab
5. shared
6. Click Restore

**Note:** This will use the ATVConfig.bin file created from your 1st clock and restore the config settings only.

Online URL: <http://tkb.amano.com/article.php?id=63>