

How to connect Time Guardian (TG) version 5, TG Plus, or TG Pro to Handpunch clock via Ethernet network

173 [Frank Mateo](#) Thu, Feb 17, 2011 [HandKey Terminals](#), [Time Guardian Series \(TG 5.x, TG Plus 2.x, TG Pro 4.x\)](#) 0 15829

AMANO.

Introduction

Amano recommends these instructions on how to connect Time Guardian (TG) version 5, TG Plus, or TG Pro to HandPunch (HP) Terminal via Ethernet network.

Use the following procedure:

- Set the IP, host bits (also subnet), gateway on the HP terminal
- Perform a ping test
- Using Time Guardian, from the main menu go to **edit > setup wizard**
- Click on the **Clock** tab and select **Yes, Yes, No, Yes**
- Click on the **Location/Terminal** button
- Click on the garbage can icon if it says fpt or mtx
- Click on the **Plus** icon to create a New terminal
- Enter HP in the Name field
- Select from the Term Type drop down the Model of HP terminal you are connecting to
- Click the Connection tab and select **Ethernet**

- Enter the IP address and verify **Port 3001** is entered
- Next, click on the terminal tab and select the **Add** button
- Set the terminal # = **0**
- Change the validation to **default**
- Verify that Active is checked
- Click the green check mark to Save
- Click the green check mark again to Save
- Click the green check mark again to Save
- From the TG Tree View [left-hand side] select the **Communications Module** [can be found under the "**Daily Activities**"]
- Highlight the HP terminal and use the 4 green buttons on the right-hand bottom for communication activity with the terminal.
- For example, press 2nd from left to set the time - this will test communication with the HP terminal.

Note: if this fails: tcp 3001 port may be blocked by a firewall(s).

Conclusion

Thank you for your time, and have a great day. As always, feel free to submit ideas on topics you want addressed in the Amano Knowledge Base using the comments feature.

Amano Cincinnati, Inc. reserves the right to make equipment changes and improvements which may not be reflected in this article. Portions of this article may have been updated to include the latest hardware or firmware version, if applicable. Amano assumes no liability for errors and/or omissions. If you should find any errors or unclear information, please notify Amano by posting a comment.

Customer Support Information	Call toll-free in the U.S.: 800-253-9836 (outside U.S. call 973-364-0294) or Fax: 973-364-1091 Mailing address: Amano Cincinnati, Inc., 140 Harrison Ave., Roseland, New Jersey 07068 Web site: www.amano.com/time • E-mail: support@amano.com
---	---

Online URL: <http://tkb.amano.com/article.php?id=173>