

HP Serial Connection Procedure for Time Guardian v5.0

112 [Frank Mateo](#) Thu, Jan 20, 2011 [HandKey Terminals](#), [Time Guardian Series \(TG 5.x, TG Plus 2.x, TG Pro 4.x\)](#) 0 6016

AMANO.

Introduction

The below steps establishes serial connection to handpunch terminals with Time Guardian version 5, plus, or pro

1. Connect the hp terminal to the serial port com1 or com2
2. Then on time guardian (tg), go to
3. Edit > setup
4. Clock > yes, yes, no, yes
5. Click on location terminal
6. Click garbage if says fpt or mtx
7. Press the plus sign
8. Enter hp in name
9. Choose the term type as model of your hp
10. Go to connection tab, direct
11. Select com1 or 2
12. Next tab, terminal
13. Press add
14. Terminal # to 1
15. Change validation to default
16. Verify active is checked
17. Click green check mark
18. Press green check again
19. Press green check again
20. Go to communications
21. Highlight hp
22. 4 green buttons on bottom right

23. Press 2nd from left, this will set time - to test communication

Conclusion

Thank you for your time, and have a great day. As always, feel free to submit ideas on topics you want addressed in the Amano Knowledge Base using the comments feature.

Amano Cincinnati, Inc. reserves the right to make equipment changes and improvements which may not be reflected in this article. Portions of this article may have been updated to include the latest hardware or firmware version, if applicable. Amano assumes no liability for errors and/or omissions. If you should find any errors or unclear information, please notify Amano by posting a comment.

Customer Support Information	Call toll-free in the U.S.: 800-253-9836 (outside U.S. call 973-364-0294) or Fax: 973-364-1091 Mailing address: Amano Cincinnati, Inc., 140 Harrison Ave., Roseland, New Jersey 07068 Web site: www.amano.com/time • E-mail: support@amano.com
---	---

Online URL: <http://tkb.amano.com/article.php?id=112>