

Guide to setup MTX-15 Ethernet Connection

111 [Frank Mateo](#) Wed, Sep 7, 2011 [MTX-15 Terminal](#), [Time Guardian Series \(TG 5.x, TG Plus 2.x, TG Pro 4.x\)](#) 0 7083



Introduction

MTX-15 Ethernet Terminal Connection with Time Guardian (TG) v5.0 procedure

1. Set the ip, using the dgdscvr utility ping test
2. Then on time guardian, go to Edit > setup
3. Clock > yes, yes, no, yes
4. Click on location terminal
5. Click garbage if says fpt
6. Go to connection tab, ethernet
7. Enter the ip
8. Verify port 2101
9. Next tab, terminal
10. Press the magnifying glass
11. Once serial shows, double click
12. Change validation to default
13. Verify active is checked
14. Click green check mark
15. Press green check again
16. Press green check again
17. Go to communications
18. Highlight mtx
19. 4 green buttons on bottom right
20. Press 2nd from left, this will set time - to test communication

Note: If this procedure fails, tcp port 2101 may be blocked by the firewall

Conclusion

Thank you for your time, and have a great day. As always, feel free to submit ideas on topics you want addressed in the Amano Knowledge Base using the comments feature.

Amano Cincinnati, Inc. reserves the right to make equipment changes and improvements which may not be reflected in this article. Portions of this article may have been updated to include the latest hardware or firmware version, if applicable. Amano assumes no liability for errors and/or omissions. If you should find any errors or unclear information, please notify Amano by posting a comment.

Customer Support Information	Call toll-free in the U.S.: 800-253-9836 (outside U.S. call 973-364-0294) or Fax: 973-364-1091 Mailing address: Amano Cincinnati, Inc., 140 Harrison Ave., Roseland, New Jersey 07068 Web site: www.amano.com/time • E-mail: support@amano.com
---	---

Online URL: <http://tkb.amano.com/article.php?id=111>